


1	General information	Supplier's name or trade mark			
2		Supplier's address	ADEO Services, 135 rue Sadi Carnot - CS00001, 59790 RONCHIN		
3		Model Identifier - Luminaire Supplier reference	C210555201/C210555201-B		
4		Light sources maker model	DLB-0921		
5		Date of placement on the market	23/03/2022		
6	Type of light source:	Lighting technology used:	LED		
7		Light source cap type (or other electric interface)	connecting leads		
8		Non-directional (NDLS) or directional (DLS):	NDLS		
9		Mains (MLS) or non-mains (NMLS):	NMLS		
10		Connected light source (CLS):	no		
11		Colour-tuneable light source:	no		
12		Envelope:	no		
13		High luminance light source:	no		
14		Anti-glare shield:	no		
15		Dimmable:	only with specific dimmers		
16	General product parameters:	Energy consumption in on-mode (kWh/1000 h)	13	kWh/1000h	
17		Energy efficiency class	D		
18		Useful luminous flux (Φ_{use}), indicating if it refers to the flux in a sphere (360°), in a wide cone (120°) or in a narrow cone (90°),	1859	360	
19		Correlated colour type	range		
20		Correlated colour temperature, rounded to the nearest 100 K, or the range of correlated colour temperatures, rounded to the nearest 100 K,	3000-6500(range)	K	
21		On-mode power (P_{on}), expressed in W and rounded to the first decimal	12.6	W	
22		Standby power (P_{sb}), expressed in W and rounded to the second decimal	0.00	W	
23		Networked standby power (P_{net}) for CLS, expressed in W and rounded to the second decimal	0.00	W	
24		Colour rendering index, rounded to the nearest integer, or the range of CRI-values that can be set	80		
25		Outer dimensions without separate control gear, lighting control parts and nonlighting control parts, if any (millimetre)			
26		Height (mm)	1010.00	mm	
27		Width (mm)	12.00	mm	
28		Depth (mm)	1.10	mm	
29			Spectral power distribution in the range 250 nm to 800 nm, at full-load (insert picture of the spectral power distribution + name of picture+extension (.jpeg))	C210555201_C210555201-B_spectral power distribution 	
30		Claim of equivalent power	-		
31		If yes, equivalent power (W)	W		
32		Chromaticity coordinates (x and y)	X=0.440, Y=0.403		
33	Parameters for directional light sources:	Peak luminous intensity (cd)		cd	
34		Beam angle in degrees (no decimal), or the range of beam angles that can be set		Degrees	
35	Parameter for LED and OLED light sources:	R9 colour rendering index value	8		
36		Survival factor rounded to the second decimal (>0.xx)	0.90		
37		Lumen maintenance factor rounded to the second decimal (>0.xx)	0.96		
38	Parameters for LED and OLED mains lights sources:	displacement factor (cos ϕ 1) rounded to the second decimal	0.00		
39		Colour consistency in McAdam ellipses	0.0		
40		Claims that an LED light source replaces a fluorescent light source without integrated ballast of a particular wattage.	-		
41		If yes then replacement claim (W) (no decimal)	0.0	W	
42		Flicker metric (Pst LM) rounded to the first decimal	1.0		
43		Stroboscopic effect metric (SVM) rounded to the first decimal	0.4		
44		Technical documentation name (in case of light source product)			
45		Light source removing instruction name (in case of containing product)	C210555201_C210555201-B_light source remove instruction.pdf		



LIGHT SOURCE REMOVING INSTRUCTION

Creation date (dd/mm/yyyy) :



23/03/2022

Last update date (dd/mm/yyyy) :

23/03/2022

1	General information	Supplier's name or trade mark	INSPIRE
2		Supplier's address	ADEO Services, 135 rue Sadi Carnot - CS0001, 59790 RONCHIN
3		Model Identifier - Luminaire Supplier reference	C210555201/C210555201-B
4		Light sources maker model	DLB-0921

Instructions on how to remove lighting control parts and/or non-lighting parts, if any, or how to switch them off or minimise their power consumption during light source testing

	Explanation of the step	Pictures	Tools
Step 1	Turn off the power		by head
Step 2	Use a screwdriver to remove the cover of the drive output, and loosen the locking screw to remove the wires. Remember the polarity color of the wires before removing them for later wiring reference.		screwdriver
Step 3	Remove the two screws securing the chassis. Remove chassis, drives, spacers, ground wires, drives, etc.		screwdriver
Step 4	Remove the silicone strip and the damaged light source		by head
Step 5	Install the light source, silicone strips, cover the light source wires with fiber tubes, tighten the fixing screws, pay attention to the driving ground wire and the yellow-green ground wire to ensure reliable grounding		screwdriver
Step 6	Connect the wires between the driver and the light source according to the wiring method in the second step and tighten the wiring screws		screwdriver
Step 7	install back bracket and turn on the light		by head