

 PRODUCT INFORMATION SHEET (ANNEX 5)		Creation date (dd/mm/yyyy) :		21/04/2023	
		Last update date (dd/mm/yyyy) :		21/04/2023	
1	General information	Supplier's name or trade mark			
2		Supplier's address		ADEO Services, 135 rue Sadi Carnot - CS00001, 59790 RONCHIN	
3		Model Identifier - Luminaire Supplier reference		W220229801-1_W220229801-2	
4		Light sources maker model		DLB-1058	
5		Date of placement on the market		21/04/2023	
6	Type of light source:	Lighting technology used:		LED	
7		Light source cap type (or other electric interface)		Direct wire	
8		Non-directional (NDLS) or directional (DLS):		NDLS	
9		Mains (MLS) or non-mains (NMLS):		NMLS	
10		Connected light source (CLS):		no	
11		Colour-tuneable light source:		no	
12		Envelope:		no	
13		High luminance light source:		no	
14		Anti-glare shield:		no	
15	Dimmable:		no		
16	General product parameters:	Energy consumption in on-mode (kWh/1000 h)		9 kWh/1000h	
17		Energy efficiency class		E	
18		Useful luminous flux (Φ_{use}), indicating if it refers to the flux in a sphere (360°), in a wide cone (120°) or in a narrow cone (90°),		1200 360	
19		Correlated colour type		steps	
20		Correlated colour temperature, rounded to the nearest 100 K, or the range of correlated colour temperatures, rounded to the nearest 100 K,		3000/4000 K	
21		On-mode power (P_{on}), expressed in W and rounded to the first decimal		9.0 W	
22		Standby power (P_{sb}), expressed in W and rounded to the second decimal		0.00 W	
23		Networked standby power (P_{net}) for CLS, expressed in W and rounded to the second decimal		0.00 W	
24		Colour rendering index, rounded to the nearest integer, or the range of CRI-values that can be set		80	
25		Outer dimensions without separate control gear, lighting control parts and nonlighting control parts, if any (millimetre)			
26		Height (mm)		540.00 mm	
27		Width (mm)		12.00 mm	
28		Depth (mm)		1.00 mm	
29		Spectral power distribution in the range 250 nm to 800 nm, at full-load (insert picture of the spectral power distribution + name of picture+extension (.jpeg))		 W220229801-1_W220229801-2_spectral power distribution	
30		Claim of equivalent power		-	
31		If yes, equivalent power (W)		W	
32		Chromaticity coordinates (x and y)		X=0.440,Y=0.403	
33		Parameters for directional light sources:	Peak luminous intensity (cd)		cd
34			Beam angle in degrees (no decimal), or the range of beam angles that can be set		Degrees
35	Parameter for LED and OLED light sources:	R9 colour rendering index value			
36		Survival factor rounded to the second decimal (>0.xx)			
37		Lumen maintenance factor rounded to the second decimal (>0.xx)			
38	Parameters for LED and OLED mains lights sources:	displacement factor (cos ϕ) rounded to the second decimal		0.50	
39		Colour consistency in McAdam ellipses		0.6	
40		Claims that an LED light source replaces a fluorescent light source without integrated ballast of a particular wattage.		-	
41		If yes then replacement claim (W) (no decimal)		0.0 W	
42		Flicker metric (Pst LM) rounded to the first decimal		1.0	
43		Stroboscopic effect metric (SVM) rounded to the first decimal		0.4	
44	Technical documentation name (in case of light source product)				
45	Light source removing instruction name (in case of containing product)		W220229801-1_W220229801-2_light source remove instruction.pdf		

		LIGHT SOURCE REMOVING INSTRUCTION		Creation date (dd/mm/yyyy) :	21/04/2023
				Last update date (dd/mm/yyyy) :	21/04/2023
1	General information	Supplier's name or trade mark	INSPIRE		
2		Supplier's address	ADEO Services, 135 rue Sadi Carnot - CS0001, 59790 RONCHIN		
3		Model Identifier - Luminaire Supplier reference	W220229801-1_ W220229801-2		
4		Light sources maker model	DLB-1058		

Instructions on how to remove lighting control parts and/or non-lighting parts, if any, or how to switch them off or minimise their power consumption during light source testing

	Explanation of the step	Pictures	Tools
Step 1	小心拔出两端塑料管封盖，并向一边拉出PC罩 Remove plastic end cut and PC cover		By hand
Step 2	用一字螺丝刀小心将光源板上的三处端子台弹片拨开，将电线拉出，再向一边方向拉出光源板 Use a flat-blade screwdriver to pull the wires out of the connection terminals, pull out the light source that needs to be replaced		screwdriver
Step 3	换上新的光源板，并依次连接电线，注意极性不能接错，并确保电线完全插入端子内，要连接可靠，不易拉出 Replace with a new light source board and connect the wires in sequence, ensuring that the wires are fully inserted into the terminals		By hand
Step 4	装好PC罩和塑料管封盖，并确保装配好 Install the PC cover and plastic end cut and ensure they are properly assembled		By hand
Step 5			
Step 6			
Step 7			