


		PRODUCT INFORMATION SHEET (ANNEX 5)		Creation date (dd/mm/yyyy) :		02/03/2023	
				Last update date (dd/mm/yyyy) :		02/03/2023	
1	General information	Supplier's name or trade mark		ADEO Services			
2		Supplier's address		ADEO Services, 135 rue Sadi Carnot - CS00001, 59790 RONCHIN			
3		Model Identifier - Luminaire Supplier reference		T061-A-366060-4D, T061-2A-366060-4D,			
4		Light sources maker model		T061-A-366060-4D-LS, T061-2A-366060-4D-LS,			
5		Date of placement on the market		17/11/2022			
6	Type of light source:	Lighting technology used:		LED			
7		Light source cap type (or other electric interface)		/			
8		Non-directional (NDLS) or directional (DLS):		NDLS			
9		Mains (MLS) or non-mains (NMLS):		NMLS			
10		Connected light source (CLS):		no			
11		Colour-tuneable light source:		no			
12		Envelope:		no			
13		High luminance light source:		no			
14		Anti-glare shield:		no			
15		Dimmable:		no			
16	General product parameters:	Energy consumption in on-mode (kWh/1000 h)		26		KWh/1000h	
17		Energy efficiency class		D			
18		Useful luminous flux (Φ_{use}), indicating if it refers to the flux in a sphere (360°), in a wide cone (120°) or in a narrow cone (90°),		3800lm		360	
19		Correlated colour type		single value			
20		Correlated colour temperature, rounded to the nearest 100 K, or the range of correlated colour temperatures, rounded to the nearest 100 K,		4000		K	
21		On-mode power (P_{on}), expressed in W and rounded to the first decimal		26.0		W	
22		Standby power (P_{sb}), expressed in W and rounded to the second decimal		0.00		W	
23		Networked standby power (P_{net}) for CLS, expressed in W and rounded to the second decimal		0.00		W	
24		Colour rendering index, rounded to the nearest integer, or the range of CRI-values that can be set		80			
25		Outer dimensions without separate control gear, lighting control parts and nonlighting control parts, if any (millimetre)					
26		Height (mm)		30.00		mm	
27		Width (mm)		595.00		mm	
28		Depth (mm)		595.00		mm	
29		Spectral power distribution in the range 250 nm to 800 nm, at full-load (insert picture of the spectral power distribution + name of picture+extension (.jpeg)		 T061-4D-spectral power distribution.jpg			
30		Claim of equivalent power		-			
31		If yes, equivalent power (W)				W	
32		Chromaticity coordinates (x and y)		0,380; 0,380			
33	Parameters for directional light sources:	Peak luminous intensity (cd)				cd	
34		Beam angle in degrees (no decimal), or the range of beam angles that can be set				Degrees	
35	Parameter for LED and OLED light sources:	R9 colour rendering index value		12.00			
36		Survival factor rounded to the second decimal (>0.xx)		0.90			
37		Lumen maintenance factor rounded to the second decimal (>0.xx)		0.93			
38	Parameters for LED and OLED mains lights sources:	displacement factor (cos ϕ 1) rounded to the second decimal					
39		Colour consistency in McAdam ellipses		6.0			
40		Claims that an LED light source replaces a fluorescent light source without integrated ballast of a particular wattage.		-			
41		If yes then replacement claim (W) (no decimal)				W	
42		Flicker metric (Pst LM) rounded to the first decimal					
43		Stroboscopic effect metric (SVM) rounded to the first decimal					
44	Technical documentation name (in case of light source product)		/				
45	Light source removing instruction name (in case of containing product)		T061-4D-LIGHT SOURCE REMOVING INSTRUCTION.pdf				



Creation date (dd/mm/yyyy) :

02/03/2023


LIGHT SOURCE REMOVING INSTRUCTION

Last update date (dd/mm/yyyy) :

02/03/2023

General information	Supplier's name or trade mark	ADEO Services
	Supplier's address	ADEO Services, 135 rue Sadi Carnot - CS00001, 59790 RONCHIN
	Model Identifier - Luminaire Supplier reference	T061-A-366060-4D, T061-2A-366060-4D, T061-A-366060-6D, T061-2A-366060-6D
	Light sources maker model	T061-A-366060-4D-LS, T061-2A-366060-4D-LS, T061-A-366060-6D-LS, T061-2A-366060-6D-LS

Instructions on how to remove lighting control parts and/or non-lighting parts, if any, or how to switch them off or minimise their power consumption during light source testing

	Explanation of the step	Pictures	Tools
Step 1	Remove backplane screws		cross screwdriver
Step 2	Remove the aluminum frame and the diffusion plate		by hand
Step 3	Disconnect the wire between the light source and the driver	 	by hand
Step 4			
Step 5			
Step 6			