

# Compact Lantern with Light Fusion Technology

**FCL412**



The *Energizer* Compact Lantern with Light Fusion Technology delivers a powerful, portable area light solution. It generates an impressively bright, 360 degree radius of illumination through its unique Light Fusion Technology. The attached carry handle folds down for added stability or can be used upright to carry or hang the light as needed. Slim, lightweight, and water resistant, this light is perfect for outdoors, camping or even power outages. With an added power-saver setting, users can extend runtime greatly. The *Energizer* Compact Lantern delivers bright uniform light and the flexibility users desire.

Lumens	Runtime	Water Ingress



DESIGN BENEFITS
<ul style="list-style-type: none"> <li>✓ Compact and Lightweight</li> <li>✓ Sturdy handle for carrying or hanging folds down for added stability</li> <li>✓ Water resistant, ideal for outdoors and camping</li> </ul>

PERFORMANCE BENEFITS
<ul style="list-style-type: none"> <li>✓ Light Fusion Technology delivers vibrant, uniform area light</li> <li>✓ 360 degree area light</li> <li>✓ High and low mode</li> </ul>

LIGHT AND POWER SOURCE
<ul style="list-style-type: none"> <li>✓ Features LED technology</li> <li>✓ Operates on 4 AA batteries</li> </ul>

BATTERY SPECIFICATIONS	
Battery Type	ENR Max Alkaline
Battery Size	AA
Number of Cells	4

PRODUCT SPECIFICATIONS	
Weight:	239 Grams / 8.4 Ounces
Dimensions:	143 mm x 192 mm x 39 mm 5.6" x 7.5" x 1.5"

BATTERY PERFORMANCE		
Modes	Lumens (lm)	Runtime (h)
High	240	8
Low	100	40

ELECTRICAL CHARACTERISTICS	
Nominal Power Consumption:	3.6 W
Batteries:	4 AA Energizer E91 3.0V dc
LED Specifications:	LED 3.0V cc / 600 mA

DISCLAIMERS
<p>Tested according to ANSI FL1 Standards.</p> <p>This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.</p>

CERTIFICATES AND COMPLIANCE
EMC, EN62471, FCC

Modes
High, Low

Publish Date: 11-09-2020

## OPERATING INSTRUCTIONS

1. Press on/off button to turn on.
2. Press 1 time for high.
3. Press 2 times for low.

## BATTERY CHANGING INSTRUCTIONS

1. Use a coin to loosen battery door screw on bottom of light.
2. Remove battery door.
3. Follow diagram on light body for battery orientation.